

WHAT IS CLAIMED IS:

1 1. In a multicarrier communication system that transmits through a band-
2 limited wireline communication channel a sequence of N-element time domain signal
3 vectors, a method of transmission, comprising;
4 estimating an impulse response convolutional model for the band limited wireline
5 communication channel to define an L-element channel vector, whereby the channel
6 output to a given one of the time domain signal vectors is modeled as being substantially
7 equal to a linear convolution of the channel vector with the respective N-element time
8 domain signal vector, plus a noise vector;
9 precoding each of a set of frequency-domain encoded data blocks using a
10 precoder to derive a set of precoded data vectors;
11 transforming each of the precoded data vectors to a respective one of the time
12 domain signal vectors; and
13 transmitting the time domain signal vectors onto the band-limited wireline
14 communication channel to be received by a far-end receiver;
15 wherein the precoder comprises:
16 a set of precoder parameters which are each at least partially derived from
17 the L-element channel vector, the precoder parameters comprising a precoder feed
18 forward parameter vector, and a precoder feed feedback parameter vector,
19 a point-wise feed forward multiplier that multiplies each element of an
20 internal precoder feed-forward vector with a corresponding element of the
21 precoder feed forward parameter vector, and
22 a point-wise feed back multiplier that multiplies each element of a
23 precoder feed-back vector with a corresponding element of the precoder feed
24 feedback parameter vector;
25 whereby the precoder performs a vector precoding operation and avoids the need
26 to compute one or more $O(N^2)$ matrix multiplication operations.

1 2. The method of claim 1, wherein the precoder further comprises a vector
2 modulo reduction unit which computes a pair of integer residues for the real and
3 imaginary components of each element of a vector applied to the input of the modulo
4 reduction unit.

1 3. The method of claim 1, wherein the precoder is embodied as a set of
2 software functions.

1 4. The method of claim 1, wherein the L-element channel vector is calculated
2 during an initial training sequence carried out with the far end receiver across the wireline
3 communication channel by sending one or more training signals through the wireline
4 communication channel and estimating the impulse response of the channel.

1 5. For use in a multicarrier communication system that transmits through a
2 band-limited wireline communication channel a sequence of N-element time domain
3 signal vectors, a transmission apparatus comprising:

4 a processor;
5 a computer readable storage medium;
6 a software instantiated in the computer readable storage medium, the software
7 comprising:

8 a first function that causes one or more training signals to be sent through
9 the wireline communication channel to a far-end receiver to cooperatively
10 estimate a set of channel parameters for a parametric model, wherein the
11 parametric model models how signals are modified by the band-limited wireline
12 communication channel as the signals pass through the band-limited wireline
13 communication channel to the far-end receiver;

14 a second function that causes a set of precoder parameters to be computed
15 at least partially based upon the channel parameters, the precoder parameters
16 comprising a precoder feed forward parameter vector and a precoder feedback
17 parameter vector,

18 a third function that causes each of a set of frequency-domain encoded
19 data blocks to be transformed to a set of precoded data vectors, wherein the third
20 function comprises:

21 a point-wise modulo reduction function that causes a set of integer
22 modulo reduction operations to be applied to each of the real and
23 imaginary components of a plurality of elements of a frequency domain
24 vector;

25 a point-wise feed forward multiplier function that causes each
26 element of an internal precoder feed-forward vector to be point-wise
27 multiplied with a corresponding element of the precoder feed forward
28 parameter vector, and
29 a point-wise feed back multiplier function that causes each element
30 of a precoder feed-back vector to be point-wise multiplied with a
31 corresponding element of the precoder feed feedback parameter vector;
32 a fourth function that causes the precoded data vectors to be transformed
33 to a respective one of the time domain signal vectors; and
34 a fifth function that causes the time domain signal vectors to be
35 transmitted onto the band-limited wireline communication channel to be received
36 by a far-end receiver.

1 6. The apparatus of claim 5, wherein the second function also computes a
2 vector of complex integer moduli to be used by the point-wise modulo reduction
3 function.

1 7. The apparatus of claim 5, wherein the third function further comprises a
2 frequency domain up-sampling function to transform an N-element frequency domain
3 vector to a 2N-element frequency domain vector.

1 8. The apparatus of claim 5, wherein at least one of the feed-forward and
2 feedback point-wise multiply functions operate on length 2N element vectors.

1 9. The apparatus of claim 5, wherein at least one of the precoder feed-
2 forward parameter vector and the precoder feedback parameter vector have 2N elements.

1 10. In a multicarrier communication system that transmits through a band-
2 limited wireline communication channel a sequence of N-element time domain signal
3 vectors, a method of transmission, comprising;
4 estimating an impulse response convolutional model for the band limited wireline
5 communication channel to define an L-element channel vector, whereby the channel
6 output to a given one of the time domain signal vectors is modeled as being substantially
7 equal to a linear convolution of the channel vector with the respective N-element time
8 domain signal vector, plus a noise vector;

9 precoding each of a set of frequency-domain encoded data blocks using a
10 precoder to derive a set of precoded data vectors, the precoder comprising a set of
11 precoder parameters which are each at least partially derived from the L-element channel
12 vector;

13 transforming each of the precoded data vectors to a respective one of the time
14 domain signal vectors; and

15 transmitting, back to back without a time domain guard interval, the time domain
16 signal vectors onto the band-limited wireline communication channel to be received by a
17 far-end receiver;

18 wherein the precoder parameters are selected and the precoding is performed to
19 compensate for time-domain inter-vector interference that would otherwise be introduced
20 by transmitting the time domain signal vectors through the band limited wireline
21 communication channel; and

22 whereby the precoder alleviates the need to insert the guard interval between
23 adjacent N-element time domain signal vectors and alleviates the need for a time domain
24 equalizer to compensate inter-vector interference between signal vectors received at a
25 receiver located at the output of the communication channel.

1 11. The method of claim 10, wherein the precoder is further selected to
2 compensate for time-domain intra-vector interference that would otherwise be introduced
3 by transmitting the time domain signal vectors through the band limited wireline
4 communication channel.

1 12. The method of claim 10, wherein the precoder is further selected to
2 modify the frequency domain power spectrum to the transmitted set of time-domain
3 signal vectors in order to meet a power constraint imposed by the wireline
4 communication system, and whereby a frequency domain equalizer located within the
5 far-end receiver can restore the original spectral properties of the encoded data using a
6 point-wise multiplication operation in the frequency domain.

1 13. The method of claim 10, wherein the L-element channel vector is
2 calculated during an initial training sequence carried out with the far end receiver across
3 the wireline communication channel by sending training signals through the wireline
4 communication channel and estimating the impulse response of the channel.

1 14. The method of claim 10, wherein the precoding involves applying a
2 nonlinear operation to each element of an intermediate frequency domain vector
3 calculated by said precoder.

1 15. The method of claim 14, wherein the nonlinear operation comprises an
2 integer arithmetic operation.

1 16. The method of claim 15, wherein the integer arithmetic operation
2 comprises a modulo reduction operation which is applied to a each of a set of frequency
3 domain vector elements and is performed according to a pair of integer moduli
4 individually selected for the real and imaginary components of each said element.

1 17. The method of claim 10, wherein the precoding involves a point-wise
2 modulo reduction operation, a feed-forward point-wise multiplication operation, and a
3 feedback point-wise multiplication operation.

1 18. The method of claim 17, wherein at least one of the feed-forward and
2 feedback point-wise multiply operations operate on length $2N$ element vectors.

1 19. In a multicarrier communication system that transmits through a band-
2 limited wireline communication channel a sequence of N -element time domain signal
3 vectors, a method of transmission, comprising;
4 sending training signals through the wireline communication channel to a far-end
5 receiver to cooperatively estimate a set of channel parameters for a parametric model,
6 wherein the parametric model models how signals are modified by the band-limited
7 wireline communication channel as the signals pass through the band-limited wireline
8 communication channel to the far-end receiver;
9 precoding each of a set of frequency-domain encoded data blocks using a
10 precoder to derive a set of precoded data vectors, the precoder comprising a set of
11 precoder parameters which are each at least partially derived from the channel
12 parameters, the precoder further comprising a point-wise modulo reduction unit that
13 applies a set of integer modulo reductions to an intermediate precoder vector in a
14 transform domain different from the time domain of the signal vectors;
15 transforming each of the precoded data vectors to a respective one of the time
16 domain signal vectors; and

17 transmitting, back to back without a time domain guard interval, the time domain
18 signal vectors onto the band-limited wireline communication channel to be received by a
19 far-end receiver;

20 wherein the precoder parameters are selected and the precoding is performed to
21 compensate for time-domain inter-vector interference that would otherwise be introduced
22 by transmitting the time domain signal vectors through the band limited wireline
23 communication channel; and

24 whereby the precoder alleviates the need to insert the guard interval between
25 adjacent N-element time domain signal vectors and alleviates the need for a time domain
26 equalizer to compensate inter-vector interference between signal vectors received at a
27 receiver located at the output of the communication channel.

1 20. The method of claim 19, wherein the precoding involves a feed-forward
2 point-wise multiplication operation, and a feedback point-wise multiplication operation. .

1 21. The method of claim 20, wherein at least one of the feed-forward and
2 feedback point-wise multiply operations operate on length $2N$ element vectors.